Note: This datasheet may be out of date  $Please \ {\it download} \ the \ latest \ data{\it sheet} \ of \ NFA21SL506X1A48\# \ from \ the \ official \ website \ of \ Murata \ Manufacturing$ 

## NFA21SL506X1A48#

"#" indicates a package specification code.








< List of part numbers with package codes > NFA21SL506X1A48B NFA21SL506X1A48L



# Appearance & Shape







# Packaging Information

Packaging	Specifications	Minimum Order Quantity
В	Bulk(Bag)	1000
L	180mm Embossed Tape 4000	



- 1. Steep insertion loss characteristics
- 2. Suitable for noise suppression in 800MHz or higher frequency
- 3. Size: 2.0x1.25mm
- 4. 4 circuits in one package

**Applications** 

Noise suppression for LCD line



		-

Other Usage

For general

## Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



1 of 3

Note: This datasheet may be out of date. Please download the latest datasheet of NFA21SL506X1A48# from the official website of Murata Manufacturing Co., Ltd.

# NFA21SL506X1A48#

"#" indicates a package specification code.



Shape	SMD	
Size Code (in mm)	2012	
Length	2.0mm	
Size Code (in inch)	0805	
Length Tolerance	±0.1mm	
Width	1.25mm	
Width Tolerance	±0.1mm	
Thickness	0.85mm	
Thickness Tolerance	±0.1mm	
Rated Current	20mA	
Operating Temperature Range	-55°C to 125°C	
Mass(typ.)	0.012g	
Number of Circuit	4	
Rated Voltage	10Vdc	
Withstanding Voltage	30Vdc	
Insulation Resistance(min.)	1000ΜΩ	
Nominal Cut-off Frequency	50MHz	
Insertion Loss	0dB to 6dB(at Cut-off Frequency),30dB min.(at 500MHz),20dB min.(at 1000MHz)	

2 of 3

## Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Note: This datasheet may be out of date


Please download the latest datasheet of NFA21SL506X1A48# from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-US/products/productdetail?partno=NFA21SL506X1A48%2

# NFA21SL506X1A48#

"#" indicates a package specification code.








Insertion Loss Characteristics

Insertion Loss Characteristics (Main Items)



**Equivalent Circuit** 

3 of 3

## Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

